



Main

For programmed and time-dependent switching of lamps.

Complementary

Functions:

- 2 independent program memories
- Pre-set switching times
- 18 programmable switching times
- Menu-controlled operation / programming
- Reserve power up to 24 hours (without battery)
- Reset to restore factory settings
- Random-check generator can be activated (in the range ± 15 mins)
- Astro function (adjustment ± 2 hours)
- Simple to switch from summer to winter time
- Timer (autom. disconnection after set time)
- Manual operation possible at any time

Nominal voltage: AC 230 V / 50 Hz

Neutral conductor: required

Switching capacity: 1000 W incandescent lamps

750 W LV halogen with electr. transformers

750 VA conv. transformer

500 VA fluorescent lamps uncomp.

400 VA fluorescent lamps with parallel comp.

1000 VA fluorescent lamps, twin-lamp circuit

Connecting terminals: Screw terminals for max. 2.5 mm² or 2x1.5 mm²

Contents: Complete device. Without frame.

Material : Thermoplastic classy matt

Colour: anthracite

The information provided in this documentation contains general descriptions and/or technical characteristics of the performance of the products contained herein. This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications. It is the duty of any such user or integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof. Neither Schneider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.